

UNIVERSITY OF WESTMINSTER



WestminsterResearch

<http://www.wmin.ac.uk/westminsterresearch>

System and circuit level design and analysis of a 16-bit sigma-delta ADC for a TETRA-2 network mobile station application.

Jaswinder Lota
Mohammed Al-Janabi
Izzet Kale

School of Informatics, University of Westminster

Copyright © [2008] IEEE. Reprinted from 2008 IEEE Instrumentation and Measurement Technology Conference Proceedings. IMTC 2008. IEEE, pp. 663-667. ISBN 9781424415403.

This material is posted here with permission of the IEEE. Such permission of the IEEE does not in any way imply IEEE endorsement of any of the University of Westminster's products or services. Internal or personal use of this material is permitted. However, permission to reprint/republish this material for advertising or promotional purposes or for creating new collective works for resale or redistribution must be obtained from the IEEE by writing to pubs-permissions@ieee.org. By choosing to view this document, you agree to all provisions of the copyright laws protecting it.

The WestminsterResearch online digital archive at the University of Westminster aims to make the research output of the University available to a wider audience. Copyright and Moral Rights remain with the authors and/or copyright owners. Users are permitted to download and/or print one copy for non-commercial private study or research. Further distribution and any use of material from within this archive for profit-making enterprises or for commercial gain is strictly forbidden.

Whilst further distribution of specific materials from within this archive is forbidden, you may freely distribute the URL of the University of Westminster Eprints (<http://www.wmin.ac.uk/westminsterresearch>).

In case of abuse or copyright appearing without permission e-mail watts@wmin.ac.uk.

System and Circuit Level Design and Analysis of a 16-Bit Sigma-Delta ADC for a TETRA-2 Network Mobile Station Application

Jaswinder Lota^{†*}, MIEEE, Mohammed Al-Janabi*, MIEEE, Izzet Kale*, MIEEE

[†]Sepura plc, Radio House, St. Andrew's Road, Cambridge CB4 1GR, UK

*Applied DSP & VLSI Research Group, Dept of Electronic Systems, University of Westminster, London, UK
jasi@ieee.org, M.Al-Janabi@wmin.ac.uk, kalei@wmin.ac.uk

Abstract: - This paper outlines a comprehensive design evaluation for development of a 16-bit Sigma-Delta (Σ - Δ) Analog-to-Digital Converter (ADC) for TETRA-2 Network Mobile Station (MS). A step-by-step design approach is described commencing from system-level evaluation leading to the circuit design, which would serve as a useful reference to designers involved with development of ADCs for wireless equipment.

I. INTRODUCTION

Terrestrial Trunked Radio (TETRA) [1] is a digital trunked mobile standard developed by the European Telecommunications Standards Institute (ETSI). The purpose of the TETRA is to meet the traditional Professional Mobile Radio (PMR) user organizations and Public Access Mobile Radio (PAMR) applications e.g. public safety (fire, ambulance and rescue services), transportation, utilities (water and electricity) and government (police, border control and military). Like GSM moving to GPRS, EDGE and UMTS/3G, due to increasing user demand for new services and facilities, the end of 2005 saw new standards being finalized as part of TETRA Release 2 [1]. The Mobile Station (MS) for the TETRA-2 applications is a Time Division Multiple Access (TDMA) based OFDM system, capable of supporting channel bandwidths of 25 kHz, 50 kHz, 100 kHz and 150 kHz [1]. A single ADC design solution therefore must be able to support a channel bandwidth of at least 150 kHz. The modulation schemes supported are $\pi/4$ DQPSK, $\pi/8$ D8PSK, 4 QAM, 16 QAM and 64 QAM.

This paper pertains to a systematic design evaluation for development of a 16-bit Σ - Δ ADC for baseband processing of TETRA-2 MS. Various Σ - Δ ADC designs have been developed to-date for GSM, CDMA and DECT applications, however the design evaluation for the TETRA-2 MS is novel as the TETRA-2 specifications are still in the process of being finalized by ETSI and to the best knowledge of the authors there is no publication on this in the open literature to date.

This paper will therefore provide a valuable reference for designers involved with the development of TETRA-2 radio equipment. A step-by-step design approach is described commencing from system-level evaluation all the way to the circuit design, which is verified by lengthy

HSPICE simulations. Section II describes the Radio Frequency (RF) Front-End (FE) assumed for the receiver. In section-III the system design is analyzed with the circuit non-idealities and nonlinear stability analysis. This is followed by simulation results in section-IV and conclusions are enumerated in section-V.

II. RECEIVER ARCHITECTURE

The receiver designs implemented for wireless applications are the superhetrodyne, low-IF or the zero-IF type [2]. The receiver assumed in this study is a conventional superhetrodyne design [2] as seen in Figure 1. The FE consists of the first-RF filter, Low Noise Amplifier (LNA), second-RF filter (Π -RF ϕ) and a mixer. The IF and baseband consist of the IF filter, the Automatic Gain Control (AGC) amplifier with a variable gain and the Quadrature Demodulator that give the In-phase and Quadrature-phase channel inputs to the respective ADCs. The Σ - Δ modulator outputs the digital samples to the SLINK filters [3], [4]. SLINK filters offer considerable advantages in terms of VLSI/hardware implementation for high sample rates [3], [4], [5]. A single-stage down-conversion from the SLINK filter, to the Root Raised Cosine (RRC) filter is employed to offer sufficient attenuation to the adjacent channel interference.

III. ADC ARCHITECTURE

The Σ - Δ ADC architecture is detailed and developed in this section. System level evaluation is undertaken for the design of the Noise Transfer Function (NTF), circuit non-idealities and nonlinear stability analysis. This is followed by the circuit design of the Σ - Δ modulator.

A. Channel Bandwidth and System Design.

The channel bandwidth requirements for the receiver determine what Dynamic Range (DR) and Effective Number of Bits (E_{NOB}) are achieved for various clock frequencies/Oversampling Ratio (OSR). The DR and the E_{NOB} are given by [6]:




Figure 1. TETRA-2 Receiver

$$DR = 10 \log \frac{3}{2} [2^B - 1]^2 \frac{(2L + 1)OSR^{2L+1}}{\pi^{2L}} \quad (1)$$

$$E_{NOB} = \frac{DR - 1.76}{6.02} \quad (2)$$

The minimum required E_{NOB} is dictated by the hardware options available in the DSP/FPGA/ASIC for the system and the RF-FE. The parameters in (1) viz., quantizer bits (B), modulator order (L) and OSR (i.e. the clock frequency) can be changed to achieve the required DR for the minimum E_{NOB} . For TETRA2 the receiver bandwidth f_B is given by (3) [1] where β is the bandwidth expansion factor having a value of 1.125, with $S_B R$ being the symbol rate of 2400 Hz, and N_{sc} the number of the sub-carriers. From (3) the bandwidths obtained are given in Table 1.

$$f_B = \beta \times S_B R \times N_{sc} \quad (3)$$

Parameters	Channel Bandwidth			
	25 kHz	50 kHz	100 kHz	150 kHz
N_{sc}	8	16	32	48
f_B (kHz)	21.6	43.2	86.4	128.6

Table 1. TETRA-2 Channel Bandwidth

Assuming a minimum required resolution of 16-bits, a 3rd-order Σ - Δ modulator would require a clock rate of 8.294 MHz, which is feasible to design and implement. The structure of a 3rd-order Σ - Δ modulator meeting the above requirements along with the coefficient values are shown in Figure 2. The single-loop 3rd-order structure is chosen since it offers a straightforward simple configuration for evaluation and implementation. The Σ - Δ modulator is designed with a lowpass NTF using the 'Cookbook' methodology [7]. The required coefficients are obtained after the desired signal scaling.




Figure 2. 3rd-order single-loop Σ - Δ modulator

B. Circuit Non-Idealities.

Incorporating the non-ideal blocks and undertaking system level simulations quantify the degradation in the Signal-to-Noise Distortion (SNDR) as a result of the circuit non-idealities. The various nonideal blocks developed in Simulink/Matlab are used for analysis [8], [9]. As a result of the non-idealities, the net reduction in the SNDR is given in Table 2.

Sl.	Parameter	Reduction in SNDR
I.	Sampling Jitter: 15 ns	1.70 dB
II.	Switch thermal Noise	0.62 dB
III.	Input-referred op-amp noise: $30 \mu V_{rms}$	1.75 dB
IV.	GBW: 11.5 MHz 100 kHz	0.00 dB 28.0 dB
V.	Slew Rate (SR): $4 V/\mu s$ $1 V/\mu s$	0.00 dB 28.0 dB
VI.	All non-idealities combined	4.50 dB

Table 2. Net reduction in SNDR

The resultant reduction in the SNDR due to all of the non-idealities considered together is 4.5 dB. Therefore the required clock frequency of the Σ - Δ modulator increases to 10.24 MHz from (1) and (2), to account for this reduction in SNDR for a minimum of 16-bit resolution in the baseband, providing us with a safety margin of 5 dB at the same time.

C. Nonlinear Stability Analyses

The NTF of the Σ - Δ modulator is given by [7]:

$$H(z) = \frac{1 - 3z^{-1} + 3z^{-2} - z^{-3}}{1 - 2.2z^{-1} + 1.688z^{-2} - 0.443z^{-3}} \quad (4)$$

The stability analysis is undertaken using the Noise Amplification Curve (A(K)) proposed in [10] and established for various Σ - Δ modulators in [11]. The $A(K)$ curve for the Σ - Δ modulator is plotted in Figure 3. The Σ - Δ modulator becomes unstable as $A(K)$ approaches the global minimum value of the curve which is 0.9 [10]. This instability sets in when the equivalent quantizer gain K has a value of 0.75. The stable amplitude limits can therefore be predicted for the NTF for DC, sinusoidal and dual-sinusoidal inputs from the quantizer gain values and the noise amplification curves as explained in [11], for which the values obtained for this Σ - Δ modulator are given in section IV.




Figure 7. QAM-4 constellation.

For QAM-16 modulation the EVM is plotted in Figure 8. The % EVM is well below the specified 10% limit for TETRA-2 [1].




Figure 8. QAM-16 Constellation.

As observed accurate mappings are produced as a result of the correct parameter selection in Table 2. The parameters can be varied in order to observe the effects of degradation, but the same has not been quantified as is considered beyond the scope of this paper.

HSPICE transient analyses were undertaken at a clock frequency of 10.24 MHz. It was observed that the predicted non-ideal SNDR response matches very closely to the SNDR response obtained from HSPICE simulations as shown in Figure 9.




Figure 9. Non-ideal Σ - Δ Modulator Response

To obtain the maximum stable input amplitude limits, simulations were undertaken at 10.24 MHz for which the values obtained are shown in Table 3.

SI	Input Signal	Stable Amplitude Limit	
		Estimated	Actual
I.	DC	0.60	0.63
II.	Sinusoidal	0.80	0.75
III.	Dual-Sine	0.35	0.36

Table 3. Stable Amplitude Limits

The stable amplitude limit obtained by HSPICE simulations for the sinusoidal signal at 7.525 kHz is plotted in Figure 10.




Figure 10. Stable Input Amplitude: Sinusoidal Signal

The step-by step approach for the design analysis in this section is given in Figure 11. Although tonal analysis has been included in the methodology, it has not been explained since the application considered is for wireless. The tonal analysis is applicable for audio applications. The tonal analysis is described in details in [12].

V. CONCLUSIONS

A comprehensive design methodology and performance evaluation of a 16-bit Σ - Δ ADC for TETRA-2 MS is presented and is validated by system and circuit level simulations. The design approach reported here would provide a valuable reference for designers involved with design of Σ - Δ ADCs for TETRA-2 receivers.




Figure 11. Steps in Design Methodology

VI. REFERENCES

- [1] ETSI TETRA-2 Design Specifications ETSI TS 100 392-2 V3.1.1 (2006-09).
- [2] Crols, J. & M.S.J. Steyaert, "Low-IF topologies for High-Performance Analog Front-End of Fully Integrated Receivers", *IEEE Trans. Circuits & Systems-II*, vol. 45, issue 3, Mar 1998, pp. 269-282.
- [3] Hogenauer, E. B., "An Economical Class of Digital Filters for Decimation & Interpolation", *IEEE Trans. ASSP*, ASSP-29(2):155-162, 1981.
- [4] Kale, I & R.C.S. Morling, "An Integrated Δ - Σ Codec for Mobile Telephone Applications", *Proc. 38th Midwest Symposium of Circuits & Systems*, vol2, pp. 945, Aug 95.
- [5] Kale, I, R.C.S. Morling & F. Custode, "DSPengine for Ultra-Low Power Audio Applications", *Proc. IEEE ISCAS 2003*, vol5, pp. 357-360, May 03.
- [6] Medeiro, F. & A. Rodriguez-Vazquez, "Design Considerations For the Δ - Σ Modulators Beyond ADSL", *Instituto de Microelectronica de Sevilla, IMSE-CNM (CSIC), Universidad de Sevilla, 41012 Sevilla, Spain*.
- [7] Norsworthy, S.R., R. Schreier & G.C. Temes, *Delta-Sigma Converters: Theory, Design & Simulation*, Wiley-IEEE Press, 1996.
- [8] Brigati, S., F. Francesconi, P. Malcoveti & F. Maloberti, "Modelling Δ - Σ Modulators Non-Idealities in Simulink", *Proc. IEEE ISCAS*, pp. 384-387, 1999.
- [9] Zare-Hoseini, H., O. Shoai, & I. Kale, "Precise Behavioral Modeling of High-Resolution Switched-Capacitor Σ - Δ Modulators", *Proc. IEEE IMTC 2004*, Como, Italy, 18-20 May 2004.
- [10] Risbo, L., "Stability Predictions for Higher-Order Sigma-Delta Modulators Based on Quasilinear Modding", *Proc. IEEE ISCAS*, Vol 5, pp. 361-364, 1994.
- [11] Lota, J., Mohammed Al-Janabi & Izzet Kale, "Nonlinear Stability Analysis of Higher-Order Δ - Σ Modulators for DC & Sinusoidal Inputs", *IEEE Transactions On Instrumentation & Measurement*, Vol 57, Issue 3, pp. 530-542, Mar 2008.
- [12] Lota, J., Mohammed Al-Janabi & Izzet Kale, "Tonality Index of Sigma-Delta Modulators: A Psychoacoustics Model Based Approach", *Proc. IEEE ISCAS 2007*, pp. 729 - 732, May 2007.